

Using Feature / Directory Number Lookup



The DX-80 system has many features and codes. At times it may be difficult to remember the code for the necessary feature. This feature code directory was implemented to aid in accessing the many features of the DX-80.

You can use the Feature/Directory Number Lookup to find the directory number and/or Feature Code and/or Suffix Codes required to operate the various system features.

Related Features

Flexible System Numbering Plan

All feature access codes

Operation

1. While the telephone is idle (no call activity), press . The display shows

DIR#/CODE LOOKUP
dir ftr suffix

2. To find a system Directory Number, press [**dir**]. The first screen of directory number listings displays. If you don't see the system resource listed press [**next**] until the resource displays, then press that interactive LCD button. (For example, to show the directory number assigned to CO Line Groups, press [**co gp**].
3. To find a system Feature Access Code, press [**ftr**]. Features are listed abbreviated and alphabetically. (Note: All codes in this list require that the button be pressed preceding the code.)
4. To find a Suffix Code, press [**suffix**]. The list of digits dialed after system resource directory numbers displays.
5. Use the [**back**] and [**next**] buttons to move through the display categories.
6. Use the Hold button to return to a previous menu level.
7. Go off-hook them on-hook (or press the ON/OFF button twice) to exit Feature/Directory Number Lookup.

List of Codes

Directory Numbers:

Feature		Directory Number(s)
Co gp (CO Line Group)	1	9
	2~8	800~806
Page (Paging)	Tenant	400
	Group 1~8	401~408
	EXT PAGE (External)	777
Hunt	Hunt/UCD Group 1~24	410~433
Pickup	Pickup Group 1~8	440~447
Music	Music Channel 1, 2	771, 772
Bell	Loud Bell/E.P./M.S.	779
Mmcf	Meet Me Conf. 1~8	390~397
Vir	Virtual Numbers 1-30	700~729
Spd	Speed Dial – Individual	470~499
	Speed Dial – System(common)	500~699
Note: These can be changed in programming.		

Feature Access Codes:

Feature	Enable Code	Disable Code
Agent Log Off	[FEATURE] 91	[FEATURE] *91
Alarm Clock	[FEATURE] 92	[FEATURE] *92
Alarm Key	[FEATURE] 62	N/A
All Forward	[FEATURE] 2	[FEATURE] 2
Attendant Administration	[FEATURE] #0	Password: 9999
Auto Hold	[FEATURE] 94	[FEATURE] *94
Auto Line Select	[FEATURE] 95	[FEATURE] *95
Auto Redial	[FEATURE] 78	N/A
Busy Forward	[FEATURE] 2	[FEATURE] 2
Busy Ring Allow	[FEATURE] #2	[FEATURE] #2
Call Forward	[FEATURE] 2	[FEATURE] 2
CBCK (Callback) Delete	[FEATURE] ##	[FEATURE] ##
CID Table	[FEATURE] 6#	Password: 9999
Conference	[FEATURE] 60	[FEATURE] 60
DB (Database) Programming	[FEATURE] #*	N/A
Default Set	[FEATURE] 69	N/A
Distinctive Ringing	[FEATURE] #7	N/A
Do Not Disturb	[FEATURE] 4	[FEATURE] 4
DSS Key Programming	[FEATURE] #4	N/A
External Call Forward	[FEATURE] 2	[FEATURE] 2
Feature Status	[FEATURE] #8	N/A
Flash	[FEATURE] 3	N/A
Follow Call Forward – From	[FEATURE] 2	[FEATURE] 2
Follow Call Forward – To	[FEATURE] 2	N/A
Forced Release (Conference)	[FEATURE] 74	N/A
Feature Code Lookup	[FEATURE] #5	N/A
Feature Key Programming	[FEATURE] #3	N/A
Feature Key Reset	[FEATURE] 58	Password: 9999
Get Held CO Line	[FEATURE] 7*	N/A
Headset Mode	[FEATURE] 9#	[FEATURE] *9#
Hidden Code	[FEATURE] 61	N/A
Hot Key	[FEATURE] #6	[FEATURE] #6
Hotline	[FEATURE] 9*	[FEATURE] *9*
ICM (Intercom) Key	[FEATURE] 65	N/A
ICM Mode (HF/Private/Ring)	[FEATURE] 98	[FEATURE] 98
Last # Redial	[FEATURE] 8	N/A
Lock Phone	[FEATURE] 97	Password: 9999
Memo Pad	[FEATURE] 5*	N/A
MSG (Message) Waiting	[FEATURE] 96	N/A
Mute Key	[FEATURE] 76	N/A
No Answer Call Forward	[FEATURE] 2	[FEATURE] 2

Feature	Enable Code	Disable Code
Paging Answer	[FEATURE] 59	N/A
Paging Receive	[FEATURE] #9	[FEATURE] #9
Park Call	[FEATURE] 73	N/A
Pause	[FEATURE] 70	N/A
Private Talk (Conference)	[FEATURE] 57	N/A
Release Key	[FEATURE] 52	N/A
Ring Mode (System Service) Note: Attendant station only	[FEATURE] 63	Password: 9999
Room Status	[FEATURE] 7#	N/A
Saved # Redial	[FEATURE] 51	N/A
Speed Dialing	[FEATURE] 1	N/A
Status MSG (Message)	[FEATURE] 90	[FEATURE] *90
Touch Tone	[FEATURE] #1	[FEATURE] #1
Unsupervised Conference	[FEATURE] 77	N/A
Voice MW Key	[FEATURE] 64	N/A
Voice Record	[FEATURE] 67	N/A

Suffix Codes:

Feature	Suffix Code
ICM Voice / Ring	*
DND Override	3
Camp On	4
Callback	#
Call Pickup	6
Intrusion	8
MSG (Message) Waiting	9
ICM (Intercom) OHVA	0
Monitor	1
Note: These can be changed.	